



SERVICE BULLETIN	
PRODUCT:	TV
BULLETIN NUMBER:	ASC20110620001
BULLETIN DATE:	6/20/2011
MODELS:	2010 LCD

SUBJECT: LCD OPTION BYTE TABLE

SYMPTOM: Issues will be apparent if the option bytes are not set properly set.

REPAIR: Option byte must be set so that the board and panel match. See the Option Byte Table for 2010 LCD.

Model Code	Side Label	Part No.					F/W directory
		Panel Module	Inverter	T-Con	Main B'd	Power	
LN19C350D1DXZA	OT01	BN07-00766A	-	-	BN96-14403A	BN44-00328A	T-SAT4AUSHC
	SY02	BN07-00703A	-	-	BN96-14409A	BN44-00328A	
	PY03	BN07-00623A	-	-	BN96-16319A	BN44-00328A	
	PT04	BN07-00941A	-	-	BN96-16398A	BN44-00328A	
LN22C350D1DXZA	BN01	BN07-00744A	-	-	BN96-14404A	BN44-00366A	
	PY02	BN07-00857A	-	-	BN96-16321A	BN44-00366A	
LN26C350D1DXZA	BN01	BN07-00866A	-	-	BN96-14407A	BN44-00368A	

This information is published for experienced repair technicians only and is not intended for use by the public. It does not contain warnings to advise non-technical individuals of possible dangers in attempting to service a product. Only experienced professional technicians should repair products powered by electricity. Any attempt to service or repair the product or products dealt with in this information by anyone else could result in serious injury or death. Information provided in this bulletin is subject to change or update without notice.

Model Code	Side Label	Option											
		Type	Model	Tuner	Region	DDR	Light Effect	Audio AMP	Ch Table	Country	Front Color	Local Set	Exhibition Mode
LN19C350D1DXZA	OT01	19O6THOC	LC350S	Xugang	US	Etron	OFF	TAS5715	-	-	NONE	other	OFF
	SY02	19A6THOC	LC350S	Xugang	US	Etron	OFF	TAS5715	-	-	NONE	other	OFF
	PY03	19I6TH0C	LC350S	ALPS	US	Etron	OFF	TAS5715	-	-	NONE	other	OFF
	PT04	19I6TH1C	LC350S	ALPS	US	Etron	OFF	TAS5715			NONE	other	OFF
LN22C350D1DXZA	BN01	22P6TH0C	LC350S	Xugang	US	Etron	OFF	TAS5715	-	-	NONE	other	OFF
	PY02	22I6TH0C	LC350S	ALPS	US	Etron	OFF	TAS5715			NONE	other	OFF
LN26C350D1DXZA	BN01	26P6AHOC	LC350	Xugang	US	Etron	OFF	TAS5715	-	-	NONE	other	OFF

Model Code	Side Label	Part No.					F/W directory
		Panel Module	Inverter	T-Con	Main B'd	Power	
LN32C350D1DXZA	BN01	BN07-00867A	-	-	BN96-14813A	BN44-00369A	T-SAT4AUSHC
	ON02	BN07-00867D	-	-	BN96-15908A	BN44-00369A	
	SQ03	BN07-00918A	-	-	BN96-15909A	BN44-00369A	
	BJ04	BN07-00867B	-	-	BN96-16395A	BN44-00369A	
	BK05	BN07-00867C	-	-	BN96-16396A	BN44-00369A	
	BN06	BN07-00867A	-	-	BN96-15907A	BN44-00369D	
	ON07	BN07-00867D	-	-	BN96-15908A	BN44-00369D	
	SQ08	BN07-00918A	-	-	BN96-15909A	BN44-00369D	
	BJ09	BN07-00867B	-	-	BN96-16395A	BN44-00369D	
	BK10	BN07-00867C	-	-	BN96-16396A	BN44-00369D	
LN19C450E1DXZA	OT01	BN07-00766A	-	-	BN96-14405A	BN44-00328A	T-SAT4AUSHC
	SY02	BN07-00703A	-	-	BN96-14410A	BN44-00328A	
	PY03	BN07-00623A	-	-	BN96-16324A	BN44-00328A	
	PT04	BN07-00941A	-	-	BN96-16551A	BN44-00328A	
LN22C450E1DXZA	CY01	BN07-00620A	-	-	BN96-14406A	BN44-00370A	
	PY02	BN07-00731A	-	-	BN96-14812A	BN44-00370A	

This information is published for experienced repair technicians only and is not intended for use by the public. It does not contain warnings to advise non-technical individuals of possible dangers in attempting to service a product. Only experienced professional technicians should repair products powered by electricity. Any attempt to service or repair the product or products dealt with in this information by anyone else could result in serious injury or death. Information provided in this bulletin is subject to change or update without notice.

Model Code	Side Label	Option											
		Type	Model	Tuner	Region	DDR	Light Effect	Audio AMP	Ch Table	Country	Front Color	Local Set	Exhibition Mode
LN32C350D1DXZA	BN01	32P6AHOC	LC350	Xugang	US	Etron	OFF	TAS5715	-	-	NONE	other	OFF
	ON02	32A6AHOC	LC350	ALPS	US	Etron	OFF	TAS5715	NONE	other	OFF		
	SQ03	32A6AHOC	LC350	ALPS	US	Etron	OFF	TAS5715	NONE	other	OFF		
	BJ04	32A6AHOC	LC350	ALPS	US	Etron	OFF	TAS5715	NONE	other	OFF		
	BK05	32P6AHOC	LC350	ALPS	US	Etron	OFF	TAS5715	NONE	other	OFF		
	BN06	32P6AHOC	LC350	ALPS	US	Etron	OFF	TAS5715			NONE	other	OFF
	ON07	32A6AHOC	LC350	ALPS	US	Etron	OFF	TAS5715			NONE	other	OFF
	SQ08	32A6AHOC	LC350	ALPS	US	Etron	OFF	TAS5715			NONE	other	OFF
	BJ09	32A6AHOC	LC350	ALPS	US	Etron	OFF	TAS5715	NONE	other	OFF		
	BK10	32P6AHOC	LC350	ALPS	US	Etron	OFF	TAS5715	NONE	other	OFF		

Model Code	Side Label	Option											
		Type	Model	Tuner	Region	DDR	Light Effect	Audio AMP	Ch Table	Country	Front Color	Local Set	Exhibition Mode
LN19C450E1DXZA	OT01	19O6TH0C	LC450	Xugang	US	ETRON	OFF	TAS5715	-	-	NONE	other	OFF
	SY02	19A6TH0C	LC450	Xugang	US	ETRON	OFF	TAS5715	-	-	NONE	other	OFF
	PY03	19I6TH0C	LC450	Xugang	US	ETRON	OFF	TAS5715			NONE	other	OFF
	PT04	19I6TH1C	LC450	Xugang	US	ETRON	OFF	TAS5715			NONE	other	OFF
LN22C450E1DXZA	CY01	22D6TH0C	LC450	Xugang	US	ETRON	OFF	TAS5715	-	-	NONE	other	OFF
	PY02	22I6TH0C	LC450	Xugang	US	ETRON	OFF	TAS5715	-	-	NONE	other	OFF

This information is published for experienced repair technicians only and is not intended for use by the public. It does not contain warnings to advise non-technical individuals of possible dangers in attempting to service a product. Only experienced professional technicians should repair products powered by electricity. Any attempt to service or repair the product or products dealt with in this information by anyone else could result in serious injury or death. Information provided in this bulletin is subject to change or update without notice.

Model Code	Side Label	Part No.					F/W directory
		Panel Module	Inverter	T-Con	Main B'd	Power	
LN26C450E1DXZA	CN02	BN07-00818A	BN81-04451A	-	BN96-14940A	BN44-00338A	T-TDT5AUSC
	AO03	BN07-00824A	BN81-04434A	-	BN96-14941A	BN44-00338A	
	CN04	BN07-00818A	BN81-04451A	-	BN96-15145A	BN44-00338A	
	AO05	BN07-00824A	BN81-04434A	-	BN96-15148A	BN44-00338A	
	SQ06	BN07-00806A	BN81-04165A	-	BN96-16397A	BN44-00338A	
LN32C450E1DXZA	CN01	BN07-00819A	BN81-04464A	-	BN96-14938A	BN44-00338B	
	AO02	BN07-00825A	BN81-04435A	-	BN96-14939A	BN44-00338B	
	SQ03	BN07-00807A	BN81-04166A	-	BN96-14913A	BN44-00338B	
	CN04	BN07-00819A	BN81-04464A	-	BN96-15146A	BN44-00338B	
	AO05	BN07-00825A	BN81-04435A	-	BN96-15147A	BN44-00338B	
	SQ06	BN07-00807A	BN81-04166A	-	BN96-14916A	BN44-00338B	
	CK07	BN07-00819B	BN81-05602A	-	BN96-15787A	BN44-00338B	
	CK08	BN07-00819B	BN81-05602A	-	BN96-16394A	BN44-00338B	
LN32C530F1FXZA	AA02	BN07-00826A	BN81-04436A	BN81-04407A	BN96-14934A	BN44-00339B	
	AA03	BN07-00826A	BN81-04436A	BN81-04407A	BN94-02617N	BN44-00339B	
	SQ04	BN07-00808A	BN81-04167A	BN81-04151A	BN96-14921A	BN44-00339B	
	SQ05	BN07-00808A	BN81-04167A	BN81-04151A	BN96-15905A	BN44-00339B	

This information is published for experienced repair technicians only and is not intended for use by the public. It does not contain warnings to advise non-technical individuals of possible dangers in attempting to service a product. Only experienced professional technicians should repair products powered by electricity. Any attempt to service or repair the product or products dealt with in this information by anyone else could result in serious injury or death. Information provided in this bulletin is subject to change or update without notice.

Model Code	Side Label	Option											
		Type	Model	Tuner	Region	DDR	Light Effect	Audio AMP	Ch Table	Country	Front Color	Local Set	Exhibition Mode
LN26C450E1DXZA	CN02	26D6AH0C	LC450	DRX3900J	-	0	OFF	-	-	USA	NONE	-	-
	AO03	26L6AH0C	LC450	DRX3900J	-	0	OFF	-	-	USA	NONE	-	-
	CN04	26D6AH0C	LC450	DRX3900J	-	0	OFF	-	-	USA	NONE	-	-
	AO05	26L6AH0C	LC450	DRX3900J	-	0	OFF	-	-	USA	NONE	-	-
	SQ06	26A6AH0C	LC450			0	OFF			USA	NONE		
LN32C450E1DXZA	CN01	32D6AH0C	LC450	DRX3900J	-	0	OFF	-	-	USA	NONE	-	-
	AO02	32L6AH0C	LC450	DRX3900J	-	0	OFF	-	-	USA	NONE	-	-
	SQ03	32A6AH0C	LC450	DRX3900J	-	0	OFF	-	-	USA	NONE	-	-
	CN04	32D6AH0C	LC450	DRX3900J	-	0	OFF	-	-	USA	NONE	-	-
	AO05	32L6AH0C	LC450	DRX3900J	-	0	OFF	-	-	USA	NONE	-	-
	SQ06	32L6AH0C	LC450	DRX3900J	-	0	OFF	-	-	USA	NONE	-	-
	CK07	Not Released											
	CK08												
LN32C530F1FXZA	AA02	32L6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	AA03	32L6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	SQ04	32A6AH0C	LC550	DRX3900J	-	0	OFF	-	-	USA	T-R-BLK	-	-
	SQ05	32A6AH0C	LC550	DRX3900J	-	0	OFF	-	-	USA	T-R-BLK	-	-

This information is published for experienced repair technicians only and is not intended for use by the public. It does not contain warnings to advise non-technical individuals of possible dangers in attempting to service a product. Only experienced professional technicians should repair products powered by electricity. Any attempt to service or repair the product or products dealt with in this information by anyone else could result in serious injury or death. Information provided in this bulletin is subject to change or update without notice.

Model Code	Side Label	Option											
		Type	Model	Tuner	Region	DDR	Light Effect	Audio AMP	Ch Table	Country	Front Color	Local Set	Exhibition Mode
LN37C530F1FXZA	AA01	37L6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	AA02	37L6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
LN40C530F1FXZA	CN01	40D6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	AA02	40L6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	CN03	40D6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	AA04	40L6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	SQ05	40A6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	SQ06	40A6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	CN07	40D6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	AA08	40L6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	SQ09	40A6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
LN46C530F1FXZA	AA01	46L6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	SQ02	46A6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	AA03	46L6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	SQ04	46A6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	AA05	46L6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	SQ06	46A6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
LN52C530F1FXZA	SQ01	52A6AF0C	LC530			0	OFF			USA	S-R-Black		
LN32C540F2DXZA	CN02	32D6AH0C	LC540	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	AO03	32L6AH0C	LC540	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	SQ04	Not Released											
	CN05	32D6AH0C	LC540	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	AO06	32L6AH0C	LC540	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-

This information is published for experienced repair technicians only and is not intended for use by the public. It does not contain warnings to advise non-technical individuals of possible dangers in attempting to service a product. Only experienced professional technicians should repair products powered by electricity. Any attempt to service or repair the product or products dealt with in this information by anyone else could result in serious injury or death. Information provided in this bulletin is subject to change or update without notice.

Model Code	Side Label	Part No.					F/W directory
		Panel Module	Inverter	T-Con	Main B'd	Power	
LN37C530F1FXZA	AA01	BN07-00828A	BN81-04438A	BN81-04409A	BN96-14935A	BN44-00339A	T-TDT5AUSC
	AA02	BN07-00828A	BN81-04438A	BN81-04409A	BN94-02617P	BN44-00339A	
LN40C530F1FXZA	CN01	BN07-00820A	BN81-04447A	BN81-04462A	BN96-14932A	BN44-00340A	
	AA02	BN07-00830A	BN81-04440A	BN81-04411A	BN96-14936A	BN44-00340A	
	CN03	BN07-00820A	BN81-04447A	BN81-04462A	BN94-02617Q	BN44-00340A	
	AA04	BN07-00830A	BN81-04440A	BN81-04411A	BN94-02617S	BN44-00340A	
	SQ05	BN07-00800A	BN81-04169A	BN81-04153A	BN96-15141A	BN44-00340A	
	SQ06	BN07-00800A	BN81-04169A	BN81-04153A	BN94-02617V	BN44-00340A	
	CN07	BN07-00820A	BN81-04447A	BN81-04462A	BN96-16390A	BN44-00417A	
	AA08	BN07-00830A	BN81-04440A	BN81-04411A	BN96-16389A	BN44-00417A	
	SQ09	BN07-00800A	BN81-04169A	BN81-04153A	BN96-16391A	BN44-00417A	
LN46C530F1FXZA	AA01	BN07-00832A	BN81-04443A	BN81-04413A	BN96-14933A	BN44-00341A	
	SQ02	BN07-00815A	BN81-04173A	BN81-04157A	BN96-14937A	BN44-00341A	
	AA03	BN07-00832A	BN81-04443A	BN81-04413A	BN94-02617R	BN44-00341A	
	SQ04	BN07-00815A	BN81-04173A	BN81-04157A	BN94-02617T	BN44-00341A	
	AA05	BN07-00832A	BN81-04443A	BN81-04413A	BN96-16392A	BN44-00418A	
	SQ06	BN07-00815A	BN81-04173A	BN81-04157A	BN96-16393A	BN44-00418A	
LN52C530F1FXZA	SQ01	BN07-00814A	BN81-04177A	BN81-04161A	BN96-14918A	BN44-00343B	
LN32C540F2DXZA	CN02	BN07-00819A	BN81-04464A	-	BN96-14952A	BN44-00338B	
	AO03	BN07-00825A	BN81-04435A	-	BN96-14949A	BN44-00338B	
	SQ04	BN07-00807A	BN81-04166A	-	BN96-14914A	BN44-00338B	
	CN05	BN07-00819A	BN81-04464A	-	BN96-15155A	BN44-00338B	
	AO06	BN07-00825A	BN81-04435A	-	BN96-15158A	BN44-00338B	
	SQ07	BN07-00807A	BN81-04166A	-	BN96-14917A	BN44-00338B	

This information is published for experienced repair technicians only and is not intended for use by the public. It does not contain warnings to advise non-technical individuals of possible dangers in attempting to service a product. Only experienced professional technicians should repair products powered by electricity. Any attempt to service or repair the product or products dealt with in this information by anyone else could result in serious injury or death. Information provided in this bulletin is subject to change or update without notice.

Model Code	Side Label	Option											
		Type	Model	Tuner	Region	DDR	Light Effect	Audio AMP	Ch Table	Country	Front Color	Local Set	Exhibition Mode
LN37C530F1FXZA	AA01	37L6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	AA02	37L6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
LN40C530F1FXZA	CN01	40D6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	AA02	40L6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	CN03	40D6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	AA04	40L6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	SQ05	40A6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	SQ06	40A6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	CN07	40D6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	AA08	40L6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	SQ09	40A6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
LN46C530F1FXZA	AA01	46L6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	SQ02	46A6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	AA03	46L6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	SQ04	46A6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	AA05	46L6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	SQ06	46A6AF0C	LC530	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
LN52C530F1FXZA	SQ01	52A6AF0C	LC530			0	OFF			USA	S-R-Black		
LN32C540F2DXZA	CN02	32D6AH0C	LC540	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	AO03	32L6AH0C	LC540	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	SQ04	Not Released											
	CN05	32D6AH0C	LC540	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	AO06	32L6AH0C	LC540	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	SQ07	Not Released											

This information is published for experienced repair technicians only and is not intended for use by the public. It does not contain warnings to advise non-technical individuals of possible dangers in attempting to service a product. Only experienced professional technicians should repair products powered by electricity. Any attempt to service or repair the product or products dealt with in this information by anyone else could result in serious injury or death. Information provided in this bulletin is subject to change or update without notice.

Model Code	Side Label	Part No.					F/W directory
		Panel Module	Inverter	T-Con	Main B'd	Power	
LN40C540F2FXZA	CN01	BN07-00820A	BN81-04447A	BN81-04462A	BN96-14950A	BN44-00340A	T-TDT5AUSC
	AA02	BN07-00830A	BN81-04440A	BN81-04411A	BN96-14951A	BN44-00340A	
	CN03	BN07-00820A	BN81-04447A	BN81-04462A	BN96-15156A	BN44-00340A	
	AA04	BN07-00830A	BN81-04440A	BN81-04411A	BN96-15159A	BN44-00340A	
	SQ05	BN07-00800A	BN81-04169A	BN81-04153A	BN96-14919A	BN44-00340A	
	SQ06	BN07-00800A	BN81-04169A	BN81-04153A	BN96-14920A	BN44-00340A	
	CN07	BN07-00820A	BN81-04447A	BN81-04462A	BN96-16371A	BN44-00417A	
	AA08	BN07-00830A	BN81-04440A	BN81-04411A	BN96-16372A	BN44-00417A	
	SQ09	BN07-00800A	BN81-04169A	BN81-04153A	BN96-16373A	BN44-00417A	
LN32C550J1FXZA	AA01	BN07-00826A	BN81-04436A	BN81-04407A	BN96-14946A	BN44-00339B	
	AA02	BN07-00826A	BN81-04436A	BN81-04407A	BN94-02700N	BN44-00339B	
	SQ03	BN07-00808A	BN81-04167A	BN81-04151A	BN96-14922A	BN44-00339B	
	SQ04	BN07-00808A	BN81-04167A	BN81-04151A	BN96-16377A	BN44-00339B	
LN37C550J1FXZA	AA01	BN07-00828A	BN81-04438A	BN81-04409A	BN96-14942A	BN44-00339A	
	AA02	BN07-00828A	BN81-04438A	BN81-04409A	BN94-02700P	BN44-00339A	
LN40C550J1FXZA	CN01	BN07-00820A	BN81-04447A	BN81-04462A	BN96-14943A	BN44-00340A	
	AA02	BN07-00830A	BN81-04440A	BN81-04411A	BN96-14947A	BN44-00340A	
	CN03	BN07-00820A	BN81-04447A	BN81-04462A	BN94-02700Q	BN44-00340A	
	AA04	BN07-00830A	BN81-04440A	BN81-04411A	BN94-02700T	BN44-00340A	
	SQ05	BN07-00800A	BN81-04169A	BN81-04153A	BN96-15665A	BN44-00340A	
	SQ06	BN07-00800A	BN81-04169A	BN81-04153A	BN96-16381A	BN44-00340A	
	CN08	BN07-00820A	BN81-04447A	BN81-04462A	BN96-16379A	BN44-00417A	
	AA09	BN07-00830A	BN81-04440A	BN81-04411A	BN96-16380A	BN44-00417A	
	SQ10	BN07-00800A	BN81-04169A	BN81-04153A	BN96-16381A	BN44-00417A	
LN46C550J1FXZA	AA01	BN07-00832A	BN81-04443A	BN81-04413A	BN96-14944A	BN44-00341A	
	SQ02	BN07-00815A	BN81-04173A	BN81-04157A	BN96-14945A	BN44-00341A	
	AA03	BN07-00832A	BN81-04443A	BN81-04413A	BN94-02700R	BN44-00341A	
	SQ04	BN07-00815A	BN81-04173A	BN81-04157A	BN94-02700S	BN44-00341A	
	AA05	BN07-00832A	BN81-04443A	BN81-04413A	BN96-16382A	BN44-00418A	
	SQ06	BN07-00815A	BN81-04173A	BN81-04157A	BN96-16383A	BN44-00418A	

This information is published for experienced repair technicians only and is not intended for use by the public. It does not contain warnings to advise non-technical individuals of possible dangers in attempting to service a product. Only experienced professional technicians should repair products powered by electricity. Any attempt to service or repair the product or products dealt with in this information by anyone else could result in serious injury or death. Information provided in this bulletin is subject to change or update without notice.

Model Code	Side Label	Option											
		Type	Model	Tuner	Region	DDR	Light Effect	Audio AMP	Ch Table	Country	Front Color	Local Set	Exhibition Mode
LN40C540F2FXZA	CN01	40D6AF0C	LC540	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	AA02	40L6AF0C	LC540	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	CN03	40D6AF0C	LC540	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	AA04	40L6AF0C	LC540	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	SQ05	40A6AF0C	LC540	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	SQ06	40A6AF0C	LC540	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	CN07	40D6AF0C	LC540	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	AA08	40L6AF0C	LC540	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
	SQ09	40A6AF0C	LC540	DRX3900J	-	0	OFF	-	-	USA	S-R-Black	-	-
LN32C550J1FXZA	AA01	32L6AF0C	LC550	DRX3900J	-	0	OFF	-	-	USA	T-R-BLK	-	-
	AA02	32L6AF0C	LC550	DRX3900J	-	0	OFF	-	-	USA	T-R-BLK	-	-
	SQ03	32A6AH0C	LC550	DRX3900J	-	0	OFF	-	-	USA	T-R-BLK	-	-
	SQ04	32A6AH0C	LC550	DRX3900J	-	0	OFF	-	-	USA	T-R-BLK	-	-
LN37C550J1FXZA	AA01	37L6AF0C	LC550	DRX3900J	-	0	OFF	-	-	USA	T-R-BLK	-	-
	AA02	37L6AF0C	LC550	DRX3900J	-	0	OFF	-	-	USA	T-R-BLK	-	-
LN40C550J1FXZA	CN01	40D6AF0C	LC550	DRX3900J	-	0	OFF	-	-	USA	T-R-BLK	-	-
	AA02	40L6AF0C	LC550	DRX3900J	-	0	OFF	-	-	USA	T-R-BLK	-	-
	CN03	40D6AF0C	LC550	DRX3900J	-	0	OFF	-	-	USA	T-R-BLK	-	-
	AA04	40L6AF0C	LC550	DRX3900J	-	0	OFF	-	-	USA	T-R-BLK	-	-
	SQ05	40A6AF0C	LC550			0	OFF			USA	T-R-BLK		
	SQ06	40A6AF0C	LC550			0	OFF			USA	T-R-BLK		

This information is published for experienced repair technicians only and is not intended for use by the public. It does not contain warnings to advise non-technical individuals of possible dangers in attempting to service a product. Only experienced professional technicians should repair products powered by electricity. Any attempt to service or repair the product or products dealt with in this information by anyone else could result in serious injury or death. Information provided in this bulletin is subject to change or update without notice.

Model Code	Side Label	Option											
		Type	Model	Tuner	Region	DDR	Light Effect	Audio AMP	Ch Table	Country	Front Color	Local Set	Exhibition Mode
LN40C550J1FXZA	CN08	40D6AF0C	LC550	DRX3900J	-	0	OFF	-	-	USA	T-R-BLK	-	-
	AA09	40L6AF0C	LC550	DRX3900J	-	0	OFF	-	-	USA	T-R-BLK	-	-
	SQ10	40A6AF0C	LC550			0	OFF			USA	T-R-BLK		
LN46C550J1FXZA	AA01	46L6AF0C	LC550	DRX3900J	-	0	OFF	-	-	USA	T-R-BLK	-	-
	SQ02	46A6AF0C	LC550	DRX3900J	-	0	OFF	-	-	USA	T-R-BLK	-	-
	AA03	46L6AF0C	LC550	DRX3900J	-	0	OFF	-	-	USA	T-R-BLK	-	-
	SQ04	46A6AF0C	LC550	DRX3900J	-	0	OFF	-	-	USA	T-R-BLK	-	-
	AA05	46L6AF0C	LC550			0	OFF			USA	T-R-BLK		
	SQ06	46A6AF0C	LC550			0	OFF			USA	T-R-BLK		

This information is published for experienced repair technicians only and is not intended for use by the public. It does not contain warnings to advise non-technical individuals of possible dangers in attempting to service a product. Only experienced professional technicians should repair products powered by electricity. Any attempt to service or repair the product or products dealt with in this information by anyone else could result in serious injury or death. Information provided in this bulletin is subject to change or update without notice.

Model Code	Side Label	Part No.					F/W directory
		Panel Module	Inverter	T-Con	Main B'd	Power	
LN40C560J1FXZA	-	-	-	-	-	-	T-VALAUSC
LN40C610N1FXZA	AA01	BN07-00831B	BN81-04442A	BN81-04466A	BN94-03446E	BN44-00340B	T-VAL5AUSC
	SQ02	BN07-00802A	BN81-04171A	BN81-04155A	BN96-19196A	BN44-00340B	
	AA03	BN07-00831B	BN81-04442A	BN81-04466A	BN94-03446K	BN44-00340B	
	SQ04	BN07-00802A	BN81-04171A	BN81-04155A	BN94-03446L	BN44-00340B	
	AA05	BN07-00831B	BN81-04442A	BN81-04466A	BN94-03446K	BN44-00340A	
	AA06	BN07-00831B	BN81-04442A	BN81-04466A	BN96-19195A	BN44-00340A	
	SQ07	BN07-00802A	BN81-04171A	BN81-04155A	BN94-03446L	BN44-00340A	
	SQ08	BN07-00802A	BN81-04171A	BN81-04155A	BN96-19196A	BN44-00340A	
LN46C610N1FXZA	SQ01	BN07-00804A	BN81-04175A	BN81-04159A	BN94-03446F	BN44-00341B	
	AA02	BN07-00833B	BN81-04445A	BN81-04467A	BN96-19198A	BN44-00341B	
	SQ03	BN07-00804A	BN81-04175A	BN81-04159A	BN44-03446M	BN44-00341B	
	AA04	BN07-00833B	BN81-04445A	BN81-04467A	BN44-03446N	BN44-00341B	
	AA05	BN07-00833B	BN81-04445A	BN81-04467A	BN44-03446N	BN44-00341A	
	AA06	BN07-00833B	BN81-04445A	BN81-04467A	BN96-19198A	BN44-00341A	
	SQ07	BN07-00804A	BN81-04175A	BN81-04159A	BN44-03446M	BN44-00341A	
	SQ08	BN07-00804A	BN81-04175A	BN81-04159A	BN96-19197A	BN44-00341A	
LN55C610N1FXZA	SQ01	BN07-00810A	BN81-04178A	BN81-04162A	BN94-03446D	BN44-00342B	
	AA02	BN07-00834A	BN81-04446A	BN81-04415A	BN96-19200A	BN44-00342B	
	SQ03	BN07-00810A	BN81-04178A	BN81-04162A	BN94-03446P	BN44-00342B	
	AA04	BN07-00834A	BN81-04446A	BN81-04415A	BN94-03446Q	BN44-00342B	
	AA05	BN07-00834A	BN81-04446A	BN81-04415A	BN94-03446Q	BN44-00342A	
	AA06	BN07-00834A	BN81-04446A	BN81-04415A	BN96-19200A	BN44-00342A	
	SQ07	BN07-00810A	BN81-04178A	BN81-04162A	BN94-03446P	BN44-00342A	
	SQ08	BN07-00810A	BN81-04178A	BN81-04162A	BN96-19199A	BN44-00342A	

This information is published for experienced repair technicians only and is not intended for use by the public. It does not contain warnings to advise non-technical individuals of possible dangers in attempting to service a product. Only experienced professional technicians should repair products powered by electricity. Any attempt to service or repair the product or products dealt with in this information by anyone else could result in serious injury or death. Information provided in this bulletin is subject to change or update without notice.

Model Code	Side Label	Option											
		Type	Model	Tuner	Region	DDR	Light Effect	Audio AMP	Ch Table	Country	Front Color	Local Set	Exhibition Mode
LN40C560J1FXZA	-	40D6AF0C	LC560	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
LN40C610N1FXZA	AA01	40L1AF0C	LC610	SEMCO	-	-	OFF	-	SAMEX	USA	T-R-BLK	-	-
	SQ02	40A1AF0C	LC610	SEMCO		-	OFF		SAMEX	USA	T-R-BLK		
	AA03	40L1AF0C	LC610	SEMCO	-	-	OFF	-	SAMEX	USA	T-R-BLK	-	-
	SQ04	40A1AF0C	LC610	SEMCO		-	OFF		SAMEX	USA	T-R-BLK		
	AA05	40L1AF0C	LC610	SEMCO	-	-	OFF	-	SAMEX	USA	T-R-BLK	-	-
	AA06	40L1AF0C	LC610	SEMCO	-	-	OFF	-	SAMEX	USA	T-R-BLK	-	-
	SQ07	40A1AF0C	LC610	SEMCO		-	OFF		SAMEX	USA	T-R-BLK		
	SQ08	40A1AF0C	LC610	SEMCO		-	OFF		SAMEX	USA	T-R-BLK		
	SQ01	46A1AF0C	LC610	SEMCO	-	-	OFF	-	SAMEX	USA	T-R-BLK	-	-
	AA02	46L1AF0C	LC610	SEMCO		-	OFF		SAMEX	USA	T-R-BLK		
LN46C610N1FXZA	SQ03	Not Released											
	AA04	46L1AF0C	LC610	SEMCO		-	OFF		SAMEX	USA	T-R-BLK		
	AA05	46L1AF0C	LC610	SEMCO		-	OFF		SAMEX	USA	T-R-BLK		
	AA06	46L1AF0C	LC610	SEMCO		-	OFF		SAMEX	USA	T-R-BLK		
	SQ07	46A1AF0C	LC610	SEMCO	-	-	OFF	-	SAMEX	USA	T-R-BLK	-	-
	SQ08	46A1AF0C	LC610	SEMCO	-	-	OFF	-	SAMEX	USA	T-R-BLK	-	-
	SQ01	55A1UF0C	LC610	SEMCO	-	-	OFF	-	SAMEX	USA	T-R-BLK	-	-
	AA02	55L1UF0C	LC610	SEMCO		-	OFF		SAMEX	USA	T-R-BLK		
LN55C610N1FXZA	SQ03	55A1UF0C	LC610	SEMCO	-	-	OFF	-	SAMEX	USA	T-R-BLK		
	AA04	55L1UF0C	LC610	SEMCO		-	OFF		SAMEX	USA	T-R-BLK		
	AA05	55L1UF0C	LC610	SEMCO		-	OFF		SAMEX	USA	T-R-BLK		

This information is published for experienced repair technicians only and is not intended for use by the public. It does not contain warnings to advise non-technical individuals of possible dangers in attempting to service a product. Only experienced professional technicians should repair products powered by electricity. Any attempt to service or repair the product or products dealt with in this information by anyone else could result in serious injury or death. Information provided in this bulletin is subject to change or update without notice.

Model Code	Side Label	Part No.					F/W directory
		Panel Module	Inverter	T-Con	Main B'd	Power	
LN40C630K1FXZA	AA01	BN07-00831B	BN81-04442A	BN81-04466A	BN94-02701F	BN44-00340B	T-VAL5AUSC
	SQ02	BN07-00802A	BN81-04171A	BN81-04155A	BN94-02701H	BN44-00340B	
	AC03	BN07-00831A	BN81-04441A	BN81-00831A	BN94-02701L	BN44-00340B	
	SS04	BN07-00801A	BN81-04170A	BN81-04154A	BN94-02701M	BN44-00340B	
	AA05	BN07-00831B	BN81-04442A	BN81-04466A	BN94-02701S	BN44-00340B	
	SQ06	BN07-00802A	BN81-04171A	BN81-04155A	BN94-02701T	BN44-00340B	
	SS09	BN07-00801A	BN81-04170A	BN81-04154A	BN96-19201A	BN44-00340A	
	SQ11	BN07-00802A	BN81-04171A	BN81-04155A	BN94-02701T	BN44-00340A	
	AA15	BN07-00831B	BN81-04442A	BN81-04466A	BN94-02701S	BN44-00340A	
	AA16	BN07-00831B	BN81-04442A	BN81-04466A	BN96-19187A	BN44-00340A	
LN46C630K1FXZA	SQ01	BN07-00804A	BN81-04175A	BN81-04159A	BN94-02701G	BN44-00341B	
	AA02	BN07-00833B	BN81-04445A	BN81-04467A	BN94-02701J	BN44-00341B	
	SS03	BN07-00816A	BN81-04174A	BN81-04158A	BN94-02701N	BN44-00341B	
	AC04	BN07-00833A	BN81-04444A	BN81-04414A	BN94-02701P	BN44-00341B	
	SQ05	BN07-00804A	BN81-04175A	BN81-04159A	BN94-02701W	BN44-00341B	
	AA06	BN07-00833B	BN81-04445A	BN81-04467A	BN94-02701X	BN44-00341B	
	AA09	BN07-00833B	BN81-04445A	BN81-04467A	BN94-02701X	BN44-00341A	
	AA10	BN07-00833B	BN81-04445A	BN81-04467A	BN96-19191A	BN44-00341A	
	SQ13	BN07-00804A	BN81-04175A	BN81-04159A	BN94-02701W	BN44-00341A	
	SQ14	BN07-00804A	BN81-04175A	BN81-04159A	BN96-19190A	BN44-00341A	
	SS16	BN07-00816A	BN81-04174A	BN81-04158A	BN96-19202A	BN44-00341A	
LN55C630K1FXZA	SQ01	BN07-00810A	BN81-04178A	BN81-04162A	BN94-02701E	BN44-00342B	
	AA02	BN07-00834A	BN81-04446A	BN81-04415A	BN96-19194A	BN44-00342B	
	SQ03	BN07-00810A	BN81-04178A	BN81-04162A	BN94-04045A	BN44-00342B	
	AA04	BN07-00834A	BN81-04446A	BN81-04415A	BN94-04045B	BN44-00342B	
	AA05	BN07-00834A	BN81-04446A	BN81-04415A	BN94-04045B	BN44-00342A	
	AA06	BN07-00834A	BN81-04446A	BN81-04415A	BN96-19194A	BN44-00342A	
	SQ07	BN07-00810A	BN81-04178A	BN81-04162A	BN94-04045A	BN44-00342A	
	SQ08	BN07-00810A	BN81-04178A	BN81-04162A	BN96-19193A	BN44-00342A	
LN60C630K1FXZA	FB01	BN07-00897A	BN81-05068A	BN81-05069A	BN94-02701K	BN44-00391A	

This information is published for experienced repair technicians only and is not intended for use by the public. It does not contain warnings to advise non-technical individuals of possible dangers in attempting to service a product. Only experienced professional technicians should repair products powered by electricity. Any attempt to service or repair the product or products dealt with in this information by anyone else could result in serious injury or death. Information provided in this bulletin is subject to change or update without notice.

Model Code	Side Label	Option											
		Type	Model	Tuner	Region	DDR	Light Effect	Audio AMP	Ch Table	Country	Front Color	Local Set	Exhibition Mode
LN40C630K1FXZA	AA01	40L1AF0C	LC630	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	SQ02	40A1AF0C	LC630	SEMCO		-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	AC03	40L1UF0C	LC630	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	SS04	40A1UF0C	LC630	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	AA05	40L1AF0C	LC630	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	SQ06	40A1AF0C	LC630	SEMCO		-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	SS09	40L1UF0C	LC630	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	SQ11	40A1AF0C	LC630	SEMCO		-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	AA15	40L1AF0C	LC630	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	AA16	40L1AF0C	LC630	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
LN46C630K1FXZA	SQ01	46A1AF0C	LC630	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	AA02	46L1AF0C	LC630	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	SS03	46A1UF0C	LC630	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	AC04	46L1UF0C	LC630	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	SQ05	46A1AF0C	LC630	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	AA06	46L1AF0C	LC630	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	AA09	46L1AF0C	LC630	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	AA10	46L1AF0C	LC630	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	SQ13	46A1AF0C	LC630	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	SQ14	46A1AF0C	LC630	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	SS16	46A1UF0C	LC630	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
LN55C630K1FXZA	SQ01	55A1UF0C	LC630	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	AA02	Not Released											
	SQ03	55A1UF0C	LC630	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	AA04	55L1UF0C	LC630	SN761640		-	OFF		SAMEX	USA	T-C-BLK		
	AA05	55L1UF0C	LC630	SN761640		-	OFF		SAMEX	USA	T-C-BLK		
	AA06	Not Released											
	SQ07	55A1UF0C	LC630	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	SQ08	55A1UF0C	LC630	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
LN60C630K1FXZA	FB01	60H1UF0C	LC630	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-

This information is published for experienced repair technicians only and is not intended for use by the public. It does not contain warnings to advise non-technical individuals of possible dangers in attempting to service a product. Only experienced professional technicians should repair products powered by electricity. Any attempt to service or repair the product or products dealt with in this information by anyone else could result in serious injury or death. Information provided in this bulletin is subject to change or update without notice.

Model Code	Side Label	Part No.					F/W directory
		Panel Module	Inverter	T-Con	Main B'd	Power	
LN40C650L1FXZA	AA01	BN07-00831A	BN81-04441A	BN81-04412A	BN94-02620N	BN44-00340B	T-VALAUSC
	SQ02	BN07-00801A	BN81-04170A	BN81-04154A	BN94-02620Q	BN44-00340B	
	AA03	BN07-00831A	BN81-04441A	BN81-04412A	BN96-19172A	BN44-00340A	
	SQ04	BN07-00801A	BN81-04170A	BN81-04154A	BN96-19175A	BN44-00340A	
LN46C650L1FXZA	SQ01	BN07-00816A	BN81-04174A	BN81-04158A	BN94-02620P	BN44-00341B	
	AA02	BN07-00833A	BN81-04444A	BN81-04414A	BN94-02620R	BN44-00341B	
	CN03	BN07-00823A	BN81-04450A	BN81-04460A	BN96-19181A	BN44-00341B	
	AA04	BN07-00833A	BN81-04444A	BN81-04414A	BN96-19176A	BN44-00341A	
	CN05	BN07-00823A	BN81-04450A	BN81-04460A	BN96-19181A	BN44-00341A	
	SQ06	BN07-00816A	BN81-04174A	BN81-04158A	BN96-19173A	BN44-00341A	
LN55C650L1FXZA	SQ01	BN07-00810A	BN81-04178A	BN81-04162A	BN94-02620J	BN44-00342B	
	AA02	BN07-00834A	BN81-04446A	BN81-04415A	BN94-02620T	BN44-00342B	
	AA04	BN07-00834A	BN81-04446A	BN81-04415A	BN96-19178A	BN44-00342A	
	SQ05	BN07-00810A	BN81-04178A	BN81-04162A	BN96-19174A	BN44-00342A	
LN40C670M1FXZA	AA01	BN07-00831A	BN81-04441A	BN81-00831A	BN94-02620L	BN44-00340B	
	SQ02	BN07-00801A	BN81-04170A	BN81-04154A	BN94-02620S	BN44-00340B	
	AA03	BN07-00831A	BN81-04441A	BN81-04412A	BN96-19170A	BN44-00340B	
	SQ04	BN07-00801A	BN81-04170A	BN81-04154A	BN96-19177A	BN44-00340A	
LN46C670M1FXZA	SQ01	BN07-00816A	BN81-04174A	BN81-04158A	BN94-02620M	BN44-00341B	
	AA02	BN07-00833A	BN81-04444A	BN81-04414A	BN94-02620U	BN44-00341B	
	CN03	BN07-00823A	BN81-04450A	BN81-04460A	BN96-19182A	BN44-00341B	
	AA04	BN07-00833A	BN81-04444A	BN81-04414A	BN96-19179A	BN44-00341A	
	CN05	BN07-00823A	BN81-04450A	BN81-04460A	BN96-19182A	BN44-00341A	
	SQ06	BN07-00816A	BN81-04174A	BN81-04158A	BN96-19171A	BN44-00341A	
LN46C750R2FXZA	SQ01	BN07-00805A	BN81-04176A	BN81-04160A	BN94-02631A	BN44-00341B	
LN55C750R2FXZA	SQ01	BN07-00812A	BN81-04180A	BN81-04164A	BN94-02631B	BN44-00342B	

This information is published for experienced repair technicians only and is not intended for use by the public. It does not contain warnings to advise non-technical individuals of possible dangers in attempting to service a product. Only experienced professional technicians should repair products powered by electricity. Any attempt to service or repair the product or products dealt with in this information by anyone else could result in serious injury or death. Information provided in this bulletin is subject to change or update without notice.

Model Code	Side Label	Option											
		Type	Model	Tuner	Region	DDR	Light Effect	Audio AMP	Ch Table	Country	Front Color	Local Set	Exhibition Mode
LN40C650L1FXZA	AA01	40L1UF0C	LC650	SEMCO	-	-	OFF	-	SAMEX	USA	T-R-BLK	-	-
	SQ02	40A1UF0C	LC650	SEMCO	-	-	OFF	-	SAMEX	USA	T-R-BLK	-	-
	AA03	40L1UF0C	LC650	SEMCO	-	-	OFF	-	SAMEX	USA	T-R-BLK	-	-
	SQ04	40A1UF0C	LC650	SEMCO	-	-	OFF	-	SAMEX	USA	T-R-BLK	-	-
LN46C650L1FXZA	SQ01	46A1UF0C	LC650	SEMCO	-	-	OFF	-	SAMEX	USA	T-R-BLK	-	-
	AA02	46L1UF0C	LC650	SEMCO	-	-	OFF	-	SAMEX	USA	T-R-BLK	-	-
	CN03	46D1UF0C	LC650	SEMCO		-	OFF		SAMEX	USA	T-R-BLK		
	AA04	46L1UF0C	LC650	SEMCO	-	-	OFF	-	SAMEX	USA	T-R-BLK	-	-
	CN05	46D1UF0C	LC650	SEMCO		-	OFF		SAMEX	USA	T-R-BLK		
	SQ06	46A1UF0C	LC650	SEMCO	-	-	OFF	-	SAMEX	USA	T-R-BLK	-	-
LN55C650L1FXZA	SQ01	55A1UF0C	LC650	SEMCO	-	-	OFF	-	SAMEX	USA	T-R-BLK	-	-
	AA02	55L1UF0C	LC650	SEMCO	-	-	OFF	-	SAMEX	USA	T-R-BLK	-	-
	AA04	55L1UF0C	LC650	SEMCO	-	-	OFF	-	SAMEX	USA	T-R-BLK	-	-
	SQ05	55A1UF0C	LC650	SEMCO	-	-	OFF	-	SAMEX	USA	T-R-BLK	-	-
LN40C670M1FXZA	AA01	40L1UF0C	LC670	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	SQ02	40A1UF0C	LC670	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	AA03	40L1UF0C	LC670	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	SQ04	40A1UF0C	LC670	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
LN46C670M1FXZA	SQ01	46A1UF0C	LC670	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	AA02	46L1UF0C	LC670	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	CN03	46L1UF0C	LC670	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	AA04	46L1UF0C	LC670	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	CN05	46L1UF0C	LC670	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
	SQ06	46A1UF0C	LC670	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
LN46C750R2FXZA	SQ01	46A2UF0C	LC750	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-
LN55C750R2FXZA	SQ01	55A2UF0C	LC750	SEMCO	-	-	OFF	-	SAMEX	USA	T-C-BLK	-	-

Note: Consult the Samsung Service Website at (service.samsungportal.com) for the Service Manual and other information on this product.

This information is published for experienced repair technicians only and is not intended for use by the public. It does not contain warnings to advise non-technical individuals of possible dangers in attempting to service a product. Only experienced professional technicians should repair products powered by electricity. Any attempt to service or repair the product or products dealt with in this information by anyone else could result in serious injury or death. Information provided in this bulletin is subject to change or update without notice.